

**WAC 51-11C-405028 Section C405.2.7—Area controls.**

**C405.2.7 Area controls.** The maximum lighting power that may be controlled from a single switch or automatic control device shall not exceed that which is provided by a 20 ampere circuit loaded to not more than 80 percent. A master control may be installed provided the individual switches retain their capability to function independently. Circuit breakers may not be used as the sole means of switching.

EXCEPTION: Areas less than 5 percent of the building footprint for footprints over 100,000 ft<sup>2</sup>.

[Statutory Authority: RCW 19.27A.025, 19.27A.045 and chapter 19.27 RCW. WSR 20-21-080, § 51-11C-405028, filed 10/19/20, effective 2/1/21. Statutory Authority: RCW 19.27A.020, 19.27A.025, 19.27A.160 and chapter 19.27 RCW. WSR 19-24-040, § 51-11C-405028, filed 11/26/19, effective 7/1/20. Statutory Authority: RCW 19.27A.025, 19.27A.160, and 19.27.074. WSR 16-03-072, § 51-11C-405028, filed 1/19/16, effective 7/1/16.]